

24-port sector antenna, 4x 694-960, 4x 1427-2690, 8x 1695-2690 MHz, 65° HPBW and 8x 3300-3800 MHz, 90° HPBW, 9x RET.

- All Internal RET actuators are connected in "Cascaded SRET" configuration
- Cluster connectors for the beam-forming array, including eight RF ports plus one calibration port
- Antenna shape optimized for wind load reduction
- S4 array uses MQ cluster connectors
- Retractable tilt indicator rods
- Includes nine internal RET's

This product will be discontinued on: December 31, 2025

General Specifications

· · · ·	
Antenna Type	Sector and beamforming
Band	Multiband
Calibration Connector Interface	MQ5
Calibration Connector Quantity	1
Color	Light Gray (RAL 7035)
Grounding Type	RF connector inner conductor and body grounded to reflector and mounting bracket
Performance Note	Outdoor usage
Radome Material	Fiberglass, UV resistant
Reflector Material	Aluminum
RF Connector Interface	4.3-10 Female MQ4 MQ5
RF Connector Location	Bottom
RF Connector Quantity, high band	8
RF Connector Quantity, mid band	12
RF Connector Quantity, low band	4
RF Connector Quantity, total	24

Remote Electrical Tilt (RET) Information

RET Hardware	CommRET v2
RET Interface	8-pin DIN Female 8-pin DIN Male

Page 1 of 6



RET Interface, quantity	2 female 2 male
Input Voltage	10-30 Vdc
Internal RET	High band (1) Low band (2) Mid band (6)
Power Consumption, active state, maximum	8 W
Power Consumption, idle state, maximum	1 W
Protocol	3GPP/AISG 2.0 (Single RET)
Dimensions	
Width	430 mm 16.929 in
Depth	197 mm 7.756 in
Length	2769 mm 109.016 in

TDD Column Spacing

2769 mm | 109.016 42 mm | 1.654 in

Array Layout

				Array ID	Frequency (MHz)	RF Connector	RET (SRET)	AISG No.	AISG RET UID
				R1	694-960	1 - 2	1	AISG1	CPxxxxxxxxxxxxxR1
				R2	694-960	3 - 4	2	AISG1	CPxxxxxxxxxxxxxR2
				¥1	1695-2690	5 - 6	3	AISG1	CPxxxxxxxxxxxxxXXXY1
¥2	¥3	¥4	¥6	¥2	1695-2690	7 - 8	4	AISG1	CPxxxxxxxxxxxxxXX2
12			10	Y3	1427-2690	9 - 10	5	AISG1	CPxxxxxxxxxxxxXXXXXY3
				¥4	1427-2690	11 - 12	6	AISG1	CPxxxxxxxxxxxxXXXY4
				Y5	1695-2690	13 - 14	7	AISG1	CPxxxxxxxxxxxxxXY5
				Y6	1695-2690	15 - 16	8	AISG1	CPxxxxxxxxxxxxXXXXY6
¥1			¥5	P1	3300-3800	17 - 24	9	AISG1	CPxxxxxxxxxxxxxxP1

(Sizes of colored boxes are not true depictions of array sizes)

Port Configuration

B2

Page 2 of 6





Electrical Specifications

Impedance	50 ohm
Operating Frequency Band	1427 – 2690 MHz 1695 – 2690 MHz 3300 – 3800 MHz 694 – 960 MHz
Polarization	±45°
Total Input Power, maximum	900 W @ 50 °C

Electrical Specifications

	R1,R2	R1,R2	R1,R2	Y3,Y4	Y3,Y4	Y3,Y4	Y1,Y2,Y5,Y	6Y1,Y2,Y5,Y	6P1
Frequency Band, MHz	694-790	790-890	880-960	1427-151	81695-220	02300-269	01695-2200	2300-2690	3300-3800
RF Port	1-4	1-4	1-4	9-12	9-12	9-12	5-8,13-16	5-8,13-16	17-24
Gain, dBi	15.6	16.2	16.4	15.5	17.3	18.3	17.1	17.9	15.7
Beamwidth, Horizontal, degrees	63	56	53	64	68	59	68	61	84
Beamwidth, Vertical, degrees	7.6	6.8	6.3	7	5.5	4.4	6	4.8	6.3
Beam Tilt, degrees	2-12	2-12	2-12	2-12	2-12	2-12	2-12	2-12	2-12
USLS (First Lobe), dB	15	16	17	16	16	18	15	18	16
Front-to-Back Ratio at 180°, dB	34	33	31	32	32	32	30	32	28

©2025 ANDREW, an Amphenol company. All rights reserved. Amphenol and ANDREW are registered trademarks of Amphenol and/or its affiliates in the U.S. and other countries. All product names, trademarks and registered trademarks are property of their respective owners. Revised: May 6, 2025



Page 3 of 6

Coupling level, Amp, Antenna port to Cal port, dB									26
Coupling level, max Amp Δ, Antenna port to Cal port, dB									±2
Coupler, max Amp Δ, Antenna port to Cal port, dB									0.9
Coupler, max Phase Δ, Antenna port to Cal port, degrees									7
Isolation, Cross Polarization, dB	27	27	27	26	26	26	27	27	25
Isolation, Inter-band, dB	27	27	27	25	26	26	27	27	25
Isolation, Co-polarization, dB									20
VSWR Return loss, dB	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0
PIM, 3rd Order, 2 x 20 W, dBc	-153	-153	-153	-153	-153	-153	-153	-153	-130
Input Power per Port at 50° C, maximum, watts	250	250	250	200	200	150	200	150	75

Electrical Specifications, Broadcast 65°

Sidelobe, dB

Frequency Band, MHz	3300-3800
Gain, dBi	18.2
Beamwidth, Horizontal, degrees	65
Beamwidth, Vertical, degrees	6.3
Front-to-Back Total Power at 180° ± 30°, dB	26
USLS (First Lobe), dB	19
Electrical Specifications, Service Beam	

Frequency Band, MHz3300–3800Steered 0° Gain, dBi20.9Steered 0° Beanwidth,
Horizontal, degrees24Steered 0° Front-to-Back
Total Power at 180° ± 30°,
dB29Steered 0° Horizontal15

Page 4 of 6



Steered 30° Gain, dBi	19.5
Steered 30° Beamwidth, Horizontal, degrees	29
Steered 30° Front-to-Back Total Power at 180° ± 30°,	26

Electrical Specifications, Soft Split

dB

Frequency Band, MHz	3300-3800
Gain, dBi	19.7
Beamwidth, Horizontal, degrees	31
Front-to-Back Total Power at 180° ± 30°, dB	27
Horizontal Sidelobe, dB	17

Mechanical Specifications

Wind Loading @ Velocity, frontal	651.0 N @ 150 km/h (146.4 lbf @ 150 km/h)
Wind Loading @ Velocity, lateral	351.0 N @ 150 km/h (78.9 lbf @ 150 km/h)
Wind Loading @ Velocity, maximum	1,028.0 N @ 150 km/h (231.1 lbf @ 150 km/h)
Wind Loading @ Velocity, rear	421.0 N @ 150 km/h (94.6 lbf @ 150 km/h)
Wind Speed, maximum	241 km/h (150 mph)

Packaging and Weights

Width, packed	530 mm 20.866 in
Depth, packed	356 mm 14.016 in
Length, packed	2897 mm 114.055 in
Weight, gross	75 kg 165.347 lb
Weight, net	53.8 kg 118.609 lb

Regulatory Compliance/Certifications

Agency	Classification
--------	----------------

ISO 9001:2015

Designed, manufactured and/or distributed under this quality management system

Included Products

BSAMNT-4

Wide Profile Antenna Downtilt Mounting Kit for 2.4 - 4.5 in (60 - 115 mm) OD round members. Kit contains one scissor top bracket set and one bottom bracket set.

Page 5 of 6



_

BSAMNT-M4

Middle Downtilt Mounting Kit for Long Antennas for 2.4 - 4.5 in (60 - 115 mm) OD round members. Kit contains one scissor bracket set.

* Footnotes

Performance Note Severe environmental conditions may degrade optimum performance

